

## TE 330

### 3PH - 3PH ONLINE UPS



#### Application areas

- Computer and Data Centers.
- Process Control in industries like CNC Lazor Printing Application
- Broadcasting
- Safety System in Power Plants
- Medical imaging Equipments like MRI, CT Scan etc.
- Elevator backup and rescue operations
- Applications requiring Constant frequency and constant voltage.

#### Product features:

- Advanced Technology: DSP based control for power and monitoring
- IGBT (insulated gate bipolar transistor) inverter technology
- Pure sine wave output
- True on-line dual conversion design for UPS
- Wide Input Range, Robust Design for Harsh Environment
- With Isolation Transformer at Output
- Engineered Design, Easy for Maintenance and Minimize MTTR
- CNC Fabricated sheet enclosure for better aesthetics and consistency
- Three phase separate control, realizes the control of instantaneous over-loading balance, so as to reach 100% unbalanced load in three phase UPS
- Intelligent communication option
- Perfect protection, Input/output over/low voltage protection displayed on LCD display with alarm function.
- Excellent load feature, It is completely capable to load from 0-100%
- Specification can be customized to suit specific requirements.

## 3PH – 3PH ONLINE UPS SYSTEMS

Specifications	
Model	TPS 330
Rating	10 KVA to 250 KVA
AC INPUT	415 V + 15% -15%, Three Phase Input
Frequency	50Hz ± 6%
DC VOLTAGE:	360/384VDC
Charging Time	12 Hours for 90% of full Capacity
Charger Type	CVCC (Constant Current Constant Voltage type)
<b>INVERTER:</b>	
Technology	DSP based, IGBT Switching
Output Voltage	380 / 400 / 415 AC Three Phase
Voltage Regulation	± 1%
Frequency	50Hz ± 0.1Hz
Waveform	PWM Sine wave
Harmonic Distortion	Less than 3% on Linear Load
Inverter Efficiency	Upto 90% till 30 KVA and upto 93% above 30 KVA
Power Factor	0.8
Overload	110 % for 1 min, 150% for 30 sec
Crest Factor	3:1
Phase Displacement	120 <sup>0</sup> ±1 <sup>0</sup>
Audible Noise	Less than 65 dB at 1 Meter
<b>DISPLAY :</b>	
Digital LCD Display for	R,Y,B Output Voltage, Output current & Frequency, DC Voltage, Battery and Load Percentage and All Faults
<b>INDICATIONS &amp;ALARMS :</b>	
a) Mains on	LED Indication
b) Inverter	LED Indication
c) Batt Low	LED Indication & Alarm
d) Fault	LED Indication & Alarm
e) Overload	LED Indication & Alarm
<b>GENERAL:</b>	
Operating temperature	0°C to 40°C
Humidity	Max 95%, Non-condensing
PROTECTIONS :	Output Overload & Short circuit, Output UV & OV, DC under & Overvoltage, Mains Under & Overvoltage, Mains Single Phasing
<b>OPTIONAL :</b>	
Communication	SNMP
Bypass	Static Switch

\*Specifications are subject to change without prior notice due to constant improvement in design & technology

\*Specification can be customized to suit specific requirement

Manufactured by



Your Own Source Of Power

B/42, Lane No.56, House No. 42/713,  
Kokan Vasat, Behind Dominos pizza,  
Chickenghar, Kalyan(w), Thane 421301

info@trivenielectric.com/  
sales@trivenielectric.com

WWW.TRIVENIELECTRIC.COM

Sales & Service By:



Made in India